

LineLED 24V - Installation Instructions

Models LIFLEX18



7777 Merrimac Ave
Niles, IL 60714
T 224.333.6033
F 224.757.7557
info@luminii.com
www.luminii.com

REV.0.3
01272026

1 / 3

Please read all instructions prior to installation and keep for future reference!

1. ILS36 MUST BE PAIRED WITH AN APPROVED LUMINII EXTRUSION
2. PRODUCT SHOULD BE INSTALLED BY A QUALIFIED ELECTRICIAN.
3. ENSURE POWER IS OFF AT FUSE BOX PRIOR TO INSTALLATION TO PREVENT ELECTRICAL SHOCK.
4. USE ONLY WITH CLASS 2 POWER UNIT.
5. SUITABLE FOR DAMP LOCATIONS.
6. FOR UNDER CABINET OR SHELF MOUNT.
7. CONFORMS TO UL STD 2108. CERTIFIED TO CSA STD C22.2 NO.250.0.

Attention: Always test LineLED Flex operation before installing. Connect LineLED to power supply to ensure it is working properly and no damage has occurred during shipping.

1 **1.1** Clean the area thoroughly where the LineLED will be installed.

Remove the paper backing from the LineLED Flex and firmly press down making sure there are no air bubbles that can cause surface irregularities to the LineLED. LineLED Flex can bend up to 90° along the bend points. **Do not remove the adhesive, removing the adhesive may cause arcing of the LineLED tape.**

NOTE - Avoid bending the LineLED Flex in sharp horizontal angles. When laying LineLED to surface avoid ripples on LineLED.

2 **2.1** If length of LineLED needs to be adjusted on site, simply cut the LED strip in between solder pads. Always cut from end with no connector / wire leads.

solder pad

LineLED 24V - Installation Instructions

Models LLFLEX18



7777 Merrimac Ave
Niles, IL 60714
T 224.333.6033
F 224.757.7557
info@luminii.com
www.luminii.com

REVO.3
01272026

2 / 3

Please read all instructions prior to installation and keep for future reference!

1. ILS36 MUST BE PAIRED WITH AN APPROVED LUMINII EXTRUSION
2. PRODUCT SHOULD BE INSTALLED BY A QUALIFIED ELECTRICIAN.
3. ENSURE POWER IS OFF AT FUSE BOX PRIOR TO INSTALLATION TO PREVENT ELECTRICAL SHOCK.
4. USE ONLY WITH CLASS 2 POWER UNIT.
5. SUITABLE FOR DAMP LOCATIONS.
6. FOR UNDER CABINET OR SHELF MOUNT.
7. CONFORMS TO UL STD 2108. CERTIFIED TO CSA STD C22.2 NO.250.0.

3

- 3.1 Place the strain relief in desired place. Make sure it is 3" away from the end of the strip.
- 3.2 Slide the zip tie through strain relief opening.
- 3.3 Lay wire lead on top of strain relief.
- 3.4 Tighten zip tie around lead wire. Cut off excess zip tie.

Labels: Screw, LL-ZIP Strain relief, Wire lead, Zip tie

Can also be placed horizontally as an option.

4

Labels: Screw, 12", 3", CL1 Mounting Clip

5

RECOMMENDED LAYOUT FOR MULTIPLE ADJACENT RUNS OF LINELED FED WITH SEPARATE POWER SUPPLIES

Position power supplies either in the middle of two runs or at the opposite ends.

Labels: power supply, LineLED

power supplies placed in the middle of two adjacent runs

power supplies placed at the opposite ends of two adjacent runs

LineLED 24V - Installation Instructions

Models LIFLEX18

Please read all instructions prior to installation and keep for future reference!

1. LLS36 MUST BE PAIRED WITH AN APPROVED LUMINII EXTRUSION
2. PRODUCT SHOULD BE INSTALLED BY A QUALIFIED ELECTRICIAN.
3. ENSURE POWER IS OFF AT FUSE BOX PRIOR TO INSTALLTION TO PREVENT ELECTRICAL SHOCK.
4. USE ONLY WITH CLASS 2 POWER UNIT.
5. SUITABLE FOR DAMP LOCATIONS.
6. FOR UNDER CABINET OR SHELF MOUNT.
7. CONFORMS TO UL STD 2108. CERTIFIED TO CSA STD C22.2 NO.250.0.



REVO.3
01272026

3 / 3



7777 Merrimac Ave
Niles, IL 60714
T 224.333.6033
F 224.757.7557
info@luminii.com
www.luminii.com

Power Supply Wiring Diagram

Note: Prior to installation all 24VDC wires must be present near fixture. Refer to the power supply installation instructions for additional information.



Static White
[Wiring Diagram PDF](#)